

## OVERVIEW

xCella's lamp control module easily plugs in to any standard outlet. It provides on/off switching of plug-in devices such as televisions, DVD players, audio/video systems, microwave ovens and computer peripherals. The XCR LCM can be easily linked with other RDT based switches or occupancy sensors to enable personalized control and increased energy efficiency.

## FEATURES

- Male plug for power input is compatible with any standard NEMA outlet
- Molded buttons with LED indicator lights for ease of configuration
- Optional mounting plate can be used to install on a wall for more secure placement

## SPECIFICATIONS

Size:	4.09" H x 1.85" W x 1.26" D (104mm x 47mm x 32mm)
Cord Lengths:	Plug cord: 3ft. (91.4cm) Outlet cord: 1ft. (30.5cm)
Weight:	12.3 oz
Mounting:	Free standing, or mounts to wall using included mounting plate
Color:	White
Wireless frequency:	902 MHz (RDT™)
Power Supply:	120VAC, 50/60Hz
Power Consumption:	1.1W @ full load, 500mW quiescent
Max Load:	General purpose - 15A @ 120VAC Resistive - 15A @ 120VAC Tungsten - 960W @ 120VAC Ballast - 600W @ 120VAC Motor Load Rating - 1/2 HP @ 120VAC
Environment:	Indoor use only 32° to 131°F (0° to 55°C) 5% to 95% relative humidity (non-condensing)

## Warranty

Five-year limited warranty. Complete warranty terms located at:

[www.acuitybrands.com/CustomerResources/Terms\\_and\\_conditions.aspx](http://www.acuitybrands.com/CustomerResources/Terms_and_conditions.aspx)

**Note:** Actual performance may differ as a result of end-user environment and application.

Specifications subject to change without notice.

**AcuityControls™**


xCella™

## Lamp Control Module




## ORDERING INFORMATION

XCR LCM	
Series	
XCR LCM	Wireless Lamp Control Module



Rocker Switch  
902MHz  
Model: XCR 1PWH  
CI Code: \*220UP4



Dual Rocker Switch  
902MHz  
Model: XCR 2PWH  
CI Code: \*220W90

**COMPLIANCE INFORMATION**

XCR LCM:FCC: SZV-STM300U  
IC: 5713A-STM300U

These devices comply with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

The intentional radiator is identical in all variants of the apparatus.

CAUTION: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

CAN RSS-Gen/CNR-Gen:  
This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada.  
To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication.

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur approuvé pour l'émetteur par Industrie Canada).  
Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
–Reorient or relocate the receiving antenna.  
–Increase the separation between the equipment and receiver.  
–Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
–Consult the dealer or an experienced radio/TV technician for help.