

Cerra 10 LED with nTune™ Technology

Frequently Asked Questions



What is the color temperature range of the Cerra 10 Tunable White?

- Cerra 10 uses Acuity's Productivity range of 3000K- 5000K or Rhythm Range 2700K-6500K.

Can I choose a color temperature in the middle of the range?

- Yes, with nLight® wallpods or SensorView programming software.

Can I order it without nLight?

- No, nTune Technology is only available on nLight. There are no 0-10v or DMX options available.

Is Cerra 10 with nTune technology compatible with existing nLight controls, graphic wallpods and sensors?

- Yes, nTune enabled Cerra 10 fixtures will work with existing nLight controls and sensors. Update to the latest version of SensorView (12.3 or newer) for system programming.

Are there any nLight wallpods specifically suited for Tunable White?

- Yes, nTune works with existing nLight dimming/scene wallpods, but we also offer a switch with "CCT" as the factory button printing (nPODM 2P DX CCT).

Is there any research supporting the link between productivity or mood and lighting?

- Contact us and we will share the information. <http://www.acuitybrands.com/about-us/contact-us>

Can I create schedules for CCT changing through an nLight controller (nECY/nGWY2)?

- Yes, the CCT is a setting that can be included in a profile.

Can the Cerra 10 with nTune technology be installed in the same nLight network as non-nTune fixtures?

- Yes, see programming guide for proper channel selection.

Can I control the Cerra 10 with nTune technology via the nLight iOS virtual wallpod app?

- Yes, the dimming and CCT color temperature can be controlled via the iOS virtual wallpod app.

Can I use the fixtures without an nLight network?

- No, the nLight network of wallpods and/or sensors is required to provide the nTune Tunable White features.

Can I use Fresco to control it?

- Yes, Fresco can control any nTune Tunable White luminaire. Update the Fresco firmware to at least version 111.

Do you offer this in a wireless control?

- At this time, nTune is only available in wired nLight technology.

Is the fixture DLC listed?

- Not at this time, DLC does not currently have a category to cover this.

Does the Cerra 10 with nTune technology provide power to the nLight network?

- No, an nPS80 or other nLight power supplying device is required to provide power to the network. The Cerra 10 with nTune technology requires the network to provide 3mA per fixture, 6mA if the fixture includes an embedded sensor.

Is this compatible with the EVO Dynamic released last fall?

- The EVO downlights use DMX for control. Fresco can control both DMX and nTune Tunable White luminaires at the same time.

Is this compatible with the BLT Tunable White and Slot Tunable White previously released?

- Yes, any luminaire with nTune Technology can work together on an nLight network.

Is there a compatible downlight with nTune technology?

- Gotham, Indy, and Aculux all offer Tunable White luminaires controlled via DMX, and a Fresco controller can combine them with any nTune luminaire in the same network.

Are these A+ Certified?

- Yes, the luminaires and controls have been tested to ensure interoperability and are designed to meet our chromatic consistency standards. Together, they are A+ Certified.